ELD series

EARTH LEAKAGE DETECTOR UNITS

A range of versatile and economical earth leakage detection relays. Each unit is housed in a robust, glass filled nylon case: an aperture in the casing allows the installation cabling to be passed through the integral core balance transformer.

The electronic circuitry combines a stable amplification of the transformer output with an ability to give high sensitivity and fast operating speeds. Detection of an earth fault results in the energisation and latching of the unit's SPCO relay. The unit is reset by momentarily removing the auxiliary supply.

Protection from excessive fault current and supply transients are fitted as standard, as is filtering to allow use with chopped waveform and variable drive applications. A 'test' facility is supplied in the form of a button, either pre-fitted into the unit's front facia or connected remotely.

Electrical connection on standard units is by a colour coded, 6 way flying lead, with terminal blocks available as an option. Each unit may be mounted on a front panel or backplate using two 3mm threaded inserts; an optional mounting assembly (part no. EMA) is also available for front access back-plate mounting.

Standard units include:

ELD2 Basic unit, with 20mS typical trip time. Fast response to earth leakage faults.

ELD4 As ELD2, but with longer trip delays, 80mS to 5 secs. Prevents nuisance tripping in motor protection circuits and allows time discrimination in distribution networks.

ELD5 As ELD4, but with an adjustable trip delay. Available in various time ranges up to 2 seconds.

With options:-

'VS' Adjustable trip current (via front facia potentiometer.)
 'HT' High temperature specification (to +60°C ambient).
 'TB' Screw terminal connectors instead of flying leads.
 'RC' Special calibration and 1m wiring for use with remote CTs (for RTCs of >125mA).

Variations on our standard units and options are also available: please call with your requirements.

When ordering, please specify:-

- a) Product type number (ELD2, ELD5, etc.)
- b) Auxiliary supply voltage
- c) Trip current (fixed, or variable range for VS option)
- d) System frequency (50, 60 or 400 Hz.)
- e) Trip delay time (fixed or variable, according to model)
- f) Additional options, if required.

Accessories:-

EMA Mounting assembly for ELD series.

Remote CTs

A range of remote core balance/current transformers, enabling specially calibrated ELD units to be used with larger cables. Available in a range of sizes, with or without a magnetic screen (see sheet M060101 for full details).




Product Specification


•	
Power supply:	
operating voltages (ranges) (all for 50/60Hz.)	110V AC (100 – 120 V) 230 V AC (200 – 250 V) 415 V AC (380 – 440 V)
power consumption	< 100mA
Control:	
trip levels trip point accuracy	fixed and variable, 10mA to 30A to BS4293
Relay output:	(ratings for resistive load)
	SPCO contacts, rated 3A @ 250V AC/30V DC, 1A @ 440V AC
Physical:	
operating temperature	standard unit: -25 to +40°C

Connection (standard unit)

weight (with EMA)



Dimensions (mm)





Frank W. Murphy Ltd. Incorporaling Modex Automation Church Road, Laverslock, Salisbury U.K. Tel: +44 1722 410085 Fax + 44 1722 410088 Pour service en Français, Lel: +44 1722 410697 email: sales@fwmurphy.co.uk web: http://www.fwmurphy.co.uk

Frank W. Murphy Ltd. en France Tel: +33 (1) 30 76 26 26 Fax: +33 (1) 30 76 39 89 Direct usine Tel: + 44 1722 410697 email: sales@fwmurphy.co.uk

email: sales/en/Minurphy, co.u.k
Frank W. Murphy Pte, Ltd.
No. 2 Tuas South Street 2, Sprintecs Building
02-01/02, Singapore 637895
Tel: + 65 863 1798 Fax: + 65 863 0208
email: fwmsales@fwmurphy.com.sg

Frank W. Murphy Southern Division PO Box 1819, Rosenberg, Texas 77471, USA Tel: +1 281 342 0297 Fax: +1 281 341 6006 email: sales@fwmurphy.com

Murphy Switch of California
PD Box 90078B, Palmdale, California 93590, USA
Tel: +1 805 272 4700 Fax: +1 805 947 7570
email: sales@murphyswitch.com
web: http://www.murphyswitch.com

Murphek Pty. Ltd. 1620 Hume Highway, Campbellfield, Vic. 3061 Australia Tel: + 61 3 9358 5555 Fax: + 61 3 9358 5558 email: murphy@macquarrie.com.au

'HT' spec.: -25 to +60°C

approx. 330 g

Murphy de Mexico S.A. de C.V.
Blvd. Anionio Rocha Cordero 300, Fracción del Aguaje
San Luis Potosí, S.L.P. México 78384
Tel: +52 48 206264 Fax: +52 48 206336
email: murmexsl@sanluis.podernel.com.mx